

Code: LED-RGB-WC/RF

LED LIGHTING CONTROLLER WITH REMOTE CONTROL **LED-RGB-WC/RF** 2.4 GHz, RGB 12 ... 24 V DC MiBOXER / Mi-Light

The LED-RGB-WC/RF lighting controller is designed to control the activation, brightness and color of the three-channel RGB LED strips. The controller is controlled using a wireless remote control operating in the 2.4 GHz band (included).

The MiBOXER controllers allow you to divide the lighting into up to 4 zones and independently control the zones using the remote control. Thanks to the repeater function, if the distance $\leq 30\text{m}$ is kept between the controllers, it is possible to transmit the control signal to controllers that are beyond the direct range of the remote control.



Application:	Works with LED lighting - (RGB) 12-24V LED strips
Rated voltage:	12 ... 24 V DC
Maximal total load:	<ul style="list-style-type: none"> • 120 W @ 12 V, • 240 W @ 24 V
Total maximal current:	6 A / Channel, 10 A (total)
Number of inputs:	1
Number of outputs:	4 (power)
Connector type:	<ul style="list-style-type: none"> • screw terminals, • 5.5/2.1 socket / screw terminals - power input
Wireless:	2.4 GHz
Radio communication range (at open area):	30 m
Mobile phones support:	—
Main features:	<ul style="list-style-type: none"> • The repeater function allows you to transfer control to subsequent LED-W-WC / LED-RGB-WC / LED-RGBW-WC modules even beyond the direct range of the remote control, • The set includes a 2.4 GHz radio remote control to control the controller, • Remote control power supply: 2x AAA 1.5V batteries (not included)
Housing:	Plastic
Color:	White
Operation temp:	-10 °C ... 40 °C
Weight:	0.05 kg
Dimensions:	85 x 45 x 22 mm
Manufacturer / Brand:	MiBOXER / Mi-Light



DATA SHEET

Guarantee:	2 years
------------	---------