

Code: EPRADO-R19-47U/600

STANDING RACK CABINET **EPRADO-R19-47U/600**

More and more home devices to LAN, RTV, CCTV installations are made with a view to the RACK system, so that their installation is aesthetically pleasing, and that devices are protected against accidental mechanical damages.

The EPRADO-R19-47U/600 cabinet is suitable for mounting all sorts of devices in standard 19" rack housings. Ideal solution for installing DVRs, power units, splitters, headends, network devices, etc. Inside the cabinet can be also place the devices that are not in standard RACK-19" housings, for example DVRs, multiswitches, RTV-SAT amplifiers, modulators. For this purpose the user should mount additional shelf/shelves available for RACK cabinet.

The RACK cabinet has many openings ensuring adequate air circulation. Additionally, it is possible to install fans to increase the ventilation.

Non-rack devices can be mounted on the four-point mounted shelves , with a depth of max. 520 mm.

Attention! The EPRADO-R19-47U/600 cabinet is intended for self-assembly.



Internal width:	19 "
Internal height:	47 U
Internal depth:	520 mm (max)
External width:	600 mm
External height:	2294 mm
External depth:	600 mm
Holes for fan coolers:	<ul style="list-style-type: none"> • 105 x 105 mm (2 places) • 340 x 260 (total size of the hole)
Bearing capacity:	800 kg
Color:	Black, RAL9004
Door:	<ul style="list-style-type: none"> • Front: glass • Side: metal, snap-in • Rear: perforated, steel



DATA SHEET

Main features:	<ul style="list-style-type: none">• Cable entries are placed from the top and bottom• From the top there are 2 cable entries with dimensions 375 x 60 mm• The floor has 6 cable entries with dimensions of 375 x 60 mm• Four rack rails for mounting devices (2x front, 2x rear)• Removable side panels• Possibility to mount the door as left or right• 4 keys included• Grounding connector• The cabinet moves on the lockable castors, stabilizing by twisting 4 leveler legs
Manufacturer / Brand:	EPRADO
Weight:	119 kg
Guarantee:	3 years