

Code: ATLO-AC-AP96

## WIRELESS PIR DETECTOR **ATLO-AC-AP96**

Wireless motion detector, which is designed to detect the moving intruder within the system protected area.



|   |  |
|---|--|
| Support:                                  | alarm control panel ATLO-AZ-WG13A-TUYA   |
| Battery power supply:                     | 1 x 9V, type 6LR61 battery (included)  |
| Frequency range:                          | 433 MHz  |
| Radio communication range (at open area): | ≥ 100 m  |
| Recommended installation height:          | 2.2 m  |
| Detection angle / Detection range:        | 110 ° / 12 m   |
| Current consumption:                      | ≤ 15 µA - Standby<br>≤ 25 mA - Alarm signaling   |
| Pet immunity:                             | < 15 kg  |
| Main features:                            | <ul style="list-style-type: none"> <li>• Code 1527 data encryption</li> <li>• Tamper detection - opening the enclosure</li> <li>• Temperature compensation</li> </ul>                                    |
| Mobile phones support:                    | Access by a cloud (P2P) <ul style="list-style-type: none"> <li>• The <a href="#">Tuya Smart</a> free application on Android</li> <li>• The <a href="#">Tuya Smart</a> free application on iOS</li> </ul> |
| Operation temp:                           | -10 °C ... 50 °C   |



# DATA SHEET

---

|                       |                  |
|-----------------------|------------------|
| Weight:               | 0.1 kg           |
| Dimensions:           | 110 x 61 x 48 mm |
| Manufacturer / Brand: | ATLO             |
| Guarantee:            | 2 years          |