

Code: K-32/LX

## WIRELESS KEYPAD **K-32/LX** PARADOX

The K-32/LX keypad is intended for daily operations and programming the PARADOX - Spectra SP series alarm control system. The keypad allows to support the systems with ability to usage the wireless devices such as e.g.: detectors, magnetic contacts, fobs without the need for additional module RTX3. With the LCD display showing text messages, even advanced functionalities of the alarm control unit are simple and convenient.



Support:	PARADOX: SPECTRA SP5500/SP6000/SP7000 V4.72+, SP4000/SP65 V4.90+
Frequency band:	433 MHz
Main features:	<ul style="list-style-type: none"> <li>• LCD 2x16 characters</li> <li>• Backlight color - Blue</li> <li>• Support StayD function</li> <li>• Buzzer for acoustic signaling of some system events</li> <li>• One-touch action buttons</li> <li>• Alarms: keypad hold-down PANIC, FIRE and AUX</li> <li>• Assign to one or more partitions</li> <li>• The ability to connect 1 alarm zone</li> <li>• Independently set chime zones</li> <li>• Connects to 4-wire communication bus</li> <li>• PGM programmable output</li> <li>• Adjustable backlight, contrast and scroll speed</li> </ul>
Compliance with standards:	ETSI EN 301 489-3, ETSI EN 300 220-2, EN 50130-4, EN 55022
Color:	White / Silver
Power supply:	12 ... 14 V DC
Current consumption:	max. 120 mA
Weight:	0.260 kg



# DATA SHEET

---

Dimensions:	123 x 144 x 33 mm
Supported languages:	Polish
Country of origin:	Canada
Manufacturer / Brand:	PARADOX
Guarantee:	2 years

