

Code: DC-200

## VOLTAGE CONVERTER **DC-200** 10 A

The DC-200 device converts the input voltage to the 12V DC value.



Type:	Decreasing the voltage, DC/DC
Power voltage:	21 V ... 30 V DC
Output voltage:	12 V ... 14 V DC
Output voltage adjustment:	—
Output current:	<ul style="list-style-type: none"> <li>• 10 A (continuous operation)</li> <li>• max. 15 A (instantaneous operation)</li> </ul>
Power:	<ul style="list-style-type: none"> <li>• 120 W (continuous operation)</li> <li>• 200 W (instantaneous operation)</li> </ul>
Protections:	<ul style="list-style-type: none"> <li>• Overvoltage,</li> <li>• Undervoltage,</li> <li>• Short-circuit</li> </ul>
Weight:	0.44 kg
Dimensions:	145 x 86 x 20 mm
Operation temp:	0 °C ... 40 °C
Guarantee:	2 years