

Code: PRF-LCD-WRL

WIRELESS KEYPAD **PRF-LCD-WRL** SATEL

The PRF-LCD-WRL keypad is intended for daily operations and programming the PERFECTA series alarm control system. With the LCD display showing text messages, even advanced functionalities of the alarm control unit are simple and convenient. Keypad is powered by battery (included) and communicates with alarm control panel using a special radio transmission protocol (bidirectional communication).



Support:	PERFECTA
Frequency band:	433 MHz
Main features:	<ul style="list-style-type: none"> • Keypad backlight buttons • LEDs indicating device operation state • Quick switch on the selected standby mode by function keys • Alarms: keypad hold-down PANIC, FIRE and AUX • Buzzer for acoustic signaling of some system events • Panel communication loss indication • Microswitch as tamper contact • Easy operation • Bidirectional encrypted radio communication
Power supply:	Lithium batteries - 2 pcs CR123A (included)
Operation temp:	-10 °C ... 55 °C
Compliance with standards:	EN 50131, Grade 2
Color:	White
Weight:	0.24 kg - Without batteries
Dimensions:	139 x 124 x 22 mm
Manufacturer / Brand:	SATEL
Guarantee:	2 years