

Code: LE-411708

RESIDUAL CURRENT CIRCUIT BREAKER **LE-411708** THREE-PHASE, AC TYPE 30 mA 40 A LEGRAND

Residual current circuit breaker with rated sensitivity of $I_{\Delta n} = 30\text{mA}$, AC type. The LE-411708 circuit breaker is compatible to DIN TS-35 rail mounting system.



Device type:	Residual current circuit breaker, Three-phase, AC type
Rated sensitivity:	30 mA
Rated current:	40 A
Number of poles:	4
Breaking capacity:	10000 A
Rated voltage:	400 V AC / 50 Hz
Connectors type:	screw terminals
Main features:	<ul style="list-style-type: none"> • Can be equipped with DX3 series signalling and remote tripping auxiliaries and motorised controls • Provided space for a label with description • Can be connected with using the supply busbars fork-type or prong-type
Housing:	Plastic, DIN, TS-35 rail mounting
Width in 17.5 mm modules:	4
Weight:	0.310 kg



DATA SHEET

Dimensions:	71 x 83 x 75 mm
Manufacturer / Brand:	LEGRAND
Guarantee:	2 years

