

Code: HDMI-SW-2/1-PIP

MULTI-VIEWER SWITCHER **HDMI-SW-2/1-PIP**

The image multi-viewer switcher allows to select one or several signal sources and connect them to the output. In addition, the device can work as a vertical image splitter, allowing simultaneous display the image from two HDMI sources with the option of selecting an active audio channel.



Number of HDMI inputs:	2 pcs
Number of HDMI outputs:	1 pcs
Supported HDMI standard:	1.3a
Supported audio formats:	LPCM, PCM2, 5.1, 7.1CH, Dolby-AC3, DTS 5.1
Max. power consumption:	5 W
Maximal transmission range:	≤ 15 m
Supported resolutions:	480i, 480p, 576i, 576p, 720p, 1080i, 1080p / 50 Hz, 1080p / 60 Hz
HDCP:	✓
Power supply:	5 V / 1 A (power adapter included)
Main features:	<ul style="list-style-type: none"> • Vertical image splitter from two sources • Displaying: only one image, two images in the same time, one image larger and the second smaller • Possibility to set the image window size • The ability to choose one of the two audio sources • Possibility to change the image window position • Control using the keys
Weight:	0.3 kg
Dimensions:	147 x 72 x 25 mm
Guarantee:	2 years