

Code: ETI-D01/10A

FUSE LINK **ETI-D01/10A** 10 A 400 V gL/gG E14 ETI

Fuse-links are used as the most reliable protection of electrical installation against overload and short-circuit currents. All fuse-links have blown-fuse indicators which are visible through the screw cap when mounted.



Rated current:	10 A
Rated voltage:	250 V DC, 400 V AC
Fusing characteristics:	gL/gG
Fuse base:	E14
Type:	D0
Size:	D01
Breaking capacity:	50000 A AC, 8000 A DC
Main features:	<ul style="list-style-type: none"> • Low power and energy losses • Small temperature increase • High ability to limit short-circuit current • Stability of current-time characteristics and full selectivity of operation • Selective cooperation with over-current circuit breakers
Housing:	Ceramic
Weight:	0.0066 kg
Dimensions:	Ø 11 x 36 mm Ø 8.5 mm (A)
Manufacturer / Brand:	ETI
Guarantee:	2 years