

Code: ETI-D02/40A

FUSE LINK **ETI-D02/40A** 40 A 400 V gL/gG E18 ETI

Fuse-links are used as the most reliable protection of electrical installation against overload and short-circuit currents. All fuse-links have blown-fuse indicators which are visible through the screw cap when mounted.



Rated current:	40 A
Rated voltage:	250 V DC, 400 V AC
Fusing characteristics:	gL/gG
Fuse base:	E18
Type:	D0
Size:	D02
Breaking capacity:	50000 A AC, 8000 A DC
Main features:	<ul style="list-style-type: none"> • Low power and energy losses • Small temperature increase • High ability to limit short-circuit current • Stability of current-time characteristics and full selectivity of operation • Selective cooperation with over-current circuit breakers
Housing:	Ceramic
Weight:	0.013 kg
Dimensions:	Ø 15 x 36 mm Ø 13.3 mm (A)
Manufacturer / Brand:	ETI
Guarantee:	2 years