

Code: PRT64MF-G

PROXIMITY READER WITH KEYPAD **PRT64MF-G** ROGER

Outdoor proximity cards and key-fobs reader. 13.56 MHz S50 standard.



Cards support:	13.56 MHz S50
Reading distance of prox-keys:	max. 6 cm
Keyboard built-in:	✓
Autonomous operation:	✓
Doorbell button:	—
Tamper output:	✓
Communication:	<ul style="list-style-type: none"> • Wiegand 26-66bit • Magstripe (Clock & Data) • RACS (Roger) and others



Main features:	<ul style="list-style-type: none"> • Tamper protection (detection of removing from mounting surface and enclosure opening) • LED indication • Beep signal • Different options of PIN codes and keyboard codes transmission • Manual or computer programming • Can be used for 13.56 MHz S50 card programming (free of charge RARC software is required) • 120 indexed users • History of 1024 events • Programmable relay output 1.5A/30V • Two transistor outputs • Two inputs NO/NC
Power supply:	10 ... 15 V DC
Average current consumption:	85 mA
Operation temp:	-25 °C ... 60 °C
Permissible relative humidity:	10 ... 95 % (non-condensing)
"Index of Protection":	IP67
Weight:	0.19 kg
Dimensions:	115 x 80 x 35 mm
Manufacturer / Brand:	ROGER
Guarantee:	3 years

