

Code: ZS600A

PROXIMITY READER WITH MEMORY **ZS600A** VIDOS

Outdoor, autonomous RFID reader.

The device allows to open the entrance by use a proximity card or keyfob. Two zones support allows to control two independent entrances (eg wicket + gate). In addition, it is possible to connect the exit button and the optical alarm detector. A PL12 IR remote controller is required for full programming (not included).

Flush mounting. Surface mounting is possible with the D600B1 cover.



Cards support:	Unique EM 125kHz
Reading distance of prox-keys:	max. 5 cm
Autonomous operation:	✓
Keyboard built-in:	—
Doorbell button:	—
Tamper output:	—
Power supply:	12 ... 15 V DC
Maximal current consumption:	150 mA
Relay contacts load:	1 A / 24 V

Main features:	• Number of relay outputs : 2 • Possibility to program up to 1010 user cards • 2 zones support, eg wicket + automatic gate • Relay to control for example: electric strike or electromagnetic lock • Optical tamper protection • Mechanical tamper protection • Watchdog built-in • Output for the additional lock release button • Possibility of working in bistable mode (close-up of the card releases the electric strike, re-closing closes it) • Reversing bolt support
Operation temp:	-20 °C ... 50 °C
Permissible relative humidity:	< 95 % (non-condensing)
"Index of Protection":	IP65
Housing:	Acid-proof steel / Plastic, Vandal-proof
Color:	Silver
Weight:	0.35 kg
Dimensions:	110 x 100 x 40 mm
Manufacturer / Brand:	VIDOS
Guarantee:	3 years