

Code: HA-129R65

AMPLIFIER WITH ACTIVE RETURN CHANNEL **HA-129R65** TERRA



Frequency range:	47 MHz ... 862 MHz
Gain :	• 24 dB ... 27 dB • 32 dB ... 36 dB selectable by switch
Gain adjustment:	17 dB
Slope adjustment:	17 dB
Maximal output level IMD3=60 dB DIN45004B:	100 dB μ V
S/N ratio:	≤ 8.5 dB

Return channel:

Frequency range:	5 MHz ... 65 MHz
Gain :	18 dB ... 21 dB
Gain adjustment:	15 dB
Maximal output level IMD3=60 dB DIN45004B:	114 dB μ V
S/N ratio:	≤ 6 dB

General information:

Number of inputs/outputs:	1 / 1 + 1 (1 x test: -30dB)
Power supply:	230 V AC



DATA SHEET

Power consumption:	≤ 4 W
Operation temp:	-20 °C ... 50 °C
Weight:	0.23 kg
Dimensions:	133 x 63 x 39 mm
Manufacturer / Brand:	TERRA
Guarantee:	2 years