

Code: PCX/AM078-L0/AM

ALARM CONTROL PANEL **PCX/AM078-L0/AM** PYRONIX

The PCX/AM078-L0/AM alarm control panel is intended for security of small and medium-sized facilities, offering comprehensive functionality in the field of security systems.



Mainboard inputs:	8 pcs
Mainboard outputs:	15 pcs
Maximal number of supported inputs:	78 pcs
Maximal number of supported outputs:	85 pcs
Users + admins:	100
Partitions:	—
Zones:	8
Events memory:	1250
Timers:	—
Supported keypads:	8 pcs (6 pcs wire)
Access from PC:	• RS-232 • PyronixCloud (PCX Insite application)
Mobile phones support:	• Android: Free application HomeControl+ • iOS: Free application HomeControl+ • Remote control of the control panel via SMS

Keyboard included:	—
Enclosure included:	✓
Protection class (Grade):	2
Power supply:	230 V AC
Operation temp:	-10 °C ... 40 °C
Weight:	5.3 kg (with enclosure and accessories)
Dimensions:	317 x 395 x 101 mm
Supported languages:	English
Manufacturer / Brand:	PYRONIX
SAP Code:	361301736
Guarantee:	2 years