

Code: BCS-V-KN

## IP / RS-485 KEYBOARD CONTROLLER **BCS-V-KN** BCS View

Network keyboard with full possibility of control and programming of the recorders and PTZ cameras from the BCS View series. Device enables quick access to the main functions, such as camera zoom and convenient 3D joystick control. Allows to control the most of camera models at direct mode (presets, routes, vectors control, etc.).

It is also possible to control many DVRs from one keyboard.



Users + admins:	15 + 1
Communication standard:	<ul style="list-style-type: none"> <li>• Ethernet, RJ-45 socket,</li> <li>• RS-485 - terminals,</li> <li>• RS-422 - terminals,</li> <li>• RS-232, D-sub socket,</li> <li>• Port USB 2.0</li> </ul>
Manipulator:	<ul style="list-style-type: none"> <li>• 4-axis joystick, Speed proportional to the swing (possibility of zoom control by joystick)</li> <li>• 1 additional button on the joystick</li> </ul>
Display:	LCD - 128 x 64 px, with light indication
PTZ control:	<ul style="list-style-type: none"> <li>• BCS View Speed Dome Cameras</li> <li>• Recorders BCS View</li> </ul>
Main features:	<ul style="list-style-type: none"> <li>• 3D PTZ support</li> <li>• Programmable buttons</li> <li>• Keyboard operation status indicator</li> <li>• Supports max. 1000 devices</li> <li>• Built-in WebService, photo capture via USB</li> </ul>
Power supply:	12 V DC / 375 mA
Power consumption:	< 4.5 W
Operation temp. / Relative humidity:	-10 °C ... 55 °C / 10 ... 90 % - (non-condensing)
Weight:	1.08 kg
Dimensions:	435 x 193 x 110 mm
Manufacturer / Brand:	BCS View



# DATA SHEET

---

Guarantee:	2 years
------------	---------