

Code: KD-137

POWER GENERATOR **KD-137** 2800 W Kraft&Dele

A power generator with manual start is perfect for emergency power supply: a central heating furnace, home, office, camping, industrial equipment, as well as on boats and yachts.

The genset engine's rubber stabilizers and engine mounts dampen vibrations and minimize noise.

The generator is equipped with a microprocessor controlled by the Smart Throttle Technology, which adjusts the engine speed to exactly match the current load. If the generator does not supply many devices, it works at a slower speed. Thus, the generator reduces fuel consumption, extending the life of the engine and increasing the runtime between refueling.

The generator is equipped with an Automatic Voltage Regulation system AVR, which allows to eliminate unfavorable voltage fluctuations to a large extent.

Attention! Maximum power on one phase (for AC 230V outlets) is approx. 0.9kW (nominal power divided by 3).



Nominal power:	2800 W Maximum power on one phase (for AC 230V outlets) is approx. 0.9kW (nominal power divided by 3)
Output voltage:	<ul style="list-style-type: none"> • 230 V AC, • 400 V AC
Number of outlets:	<ul style="list-style-type: none"> • 1 pcs - single-phase, • 1 pcs - three-phase
Built-in voltmeter:	✓
Output frequency:	50 Hz
AVR voltage stabilization:	✓
12V DC output:	✓
Engine power:	7 HP
Engine type:	4 stroke, gasoline, air cooled
Starting the engine:	Manual
Noise level during operation:	66 dB
Average fuel consumption:	1.25 l/h
Fuel tank capacity:	15 l
Fuel gauge:	✓



DATA SHEET

Material:	Stainless steel + Aluminum + Plastic
Color:	Red + Black
Weight:	41 kg
Dimensions:	620 x 450 x 450 mm
Manufacturer / Brand:	Kraft&Dele
Guarantee:	12 months