

Code: KW-I2000

INVERTER POWER GENERATOR **KW-I2000** 1800 VA KraftWele

The use of technology with the use of an inverter allows to obtain a stable output voltage that allows for safe powering of electronic receivers.

The inverter generator is used for emergency power supply, e.g. computers, server rooms, telephones, central heating furnace controllers, digitally controlled household equipment, heat pumps, electrically opened gates and garage gates, various medical devices and other devices sensitive to voltage fluctuations. It is also a convenient power supply in the field of tourism, e.g. caravans, camper-vans, boats, etc.

Device in the Silent version - very quiet generator operation at 65 dBA.



Nominal power:	1800 VA
Maximum power:	2000 VA
Output voltage:	230 V AC
Number of outlets:	1 pcs - single-phase
Built-in voltmeter:	—
Output frequency:	50 Hz
Voltage stabilization:	Inverter (provides full voltage stabilization)
12V DC output:	✓
Engine power:	3.2 kW
Engine type:	4 stroke, gasoline, air cooled
Starting the engine:	Manual
Noise level during operation:	65 dB
Average fuel consumption:	0.6 l/h



DATA SHEET

Fuel tank capacity:	4 l
Fuel gauge:	—
Material:	Plastic + Metal
Color:	Red
Weight:	19.1 kg
Dimensions:	495 x 275 x 395 mm
Manufacturer / Brand:	KraftWele
Guarantee:	2 years

