

Code: DS-PDPC12P-EG2-WE

WIRELESS PIR DETECTOR WITH CAMERA AX PRO **DS-PDPC12P-EG2-WE** Hikvision

Wireless PIR detector with camera and IR illuminator. The camera enables video verification of triggered alarm events. Viewing real-time images you can fast and accurate response to real alarm events.

The device is designed to work with the Hikvision AX PRO wireless access control systems operating in the 868 MHz band.

Attention! Device is designed for indoor use only.



Support:	Wireless alarm systems HIKVISION AX PRO
Frequency band:	868 MHz
Radio communication range (at open area):	max. 800 m
Alarm signaling:	Signal to control panel, LED
Tamper contact:	✓
Battery:	3 x CR123A 3 V (included)
Backup time:	~ 6 years
Current consumption:	max. 1500 mA 20 µA (Standby mode)
Protection class (Grade):	2
Environmental class EN 50130-5:	II

Main features:	<ul style="list-style-type: none"> • For indoor use • Bidirectional communication • AES-128 data encryption • Compliance with the Cam-X protocol • Digital detector : - SEC (Smart Environmental Control) - advanced digital signal processing and 3D optics - Detection angle : 85.9 ° - Detector range : 12 m - Pet immunity : 30 kg - Motion Detection : 0.3 ... 2 m/s - Advanced temperature compensation • Built-in camera CMOS : - Camera view angle : 88 ° - Supported resolutions : 640 x 480 px, 320 x 240 px, 160 x 120 px - Pictures recording format : JPEG - Day/night mode - IR illuminator : 12 m • Remote configuration • Wall mounting : 1.8 ... 2.4 m
Color:	White
Operation temp:	-10 °C ... 55 °C
Permissible relative humidity:	10 % ... 90 %
Weight:	0.22 kg
Dimensions:	72 x 121 x 57 mm
Manufacturer / Brand:	Hikvision
SAP Code:	314300064
Guarantee:	2 years