

Code: DS-PDSMK-S-WE

WIRELESS SMOKE DETECTOR AX PRO **DS-PDSMK-S-WE** Hikvision

Wireless smoke detector, which is designed to early detection of a developing fire. Besides sending the information to the control panel, the DS-PDSMK-S-WE detector can warn of the danger of using the built sound alarm.

The DS-PDSMK-S-WE supports the other devices compatible with wireless HIKVISION AX PRO system.



Support:	HIKVISION AX PRO
Detection:	smoke
Alarm signaling:	- Buzzer ≥ 85 dB @ 3 m - LED indicator - red - Signal to control panel
Frequency band:	868 MHz
Radio communication range (at open area):	800 m
Power supply:	1 x battery CR17450 3 V (built-in)
Backup time:	~ 10 years
Main features:	- Smoke detection - Chamber with photoelectric sensor - Signal indicator - Bidirectional communication - AES-128 data encryption - Ceiling mounting
Color:	White
Operation temp:	-10 °C ... 60 °C
Weight:	0.124 kg
Dimensions:	Ø 102 x 35 mm



DATA SHEET

Manufacturer / Brand:	Hikvision
SAP Code:	314300075
Guarantee:	2 years