

Code: TF-007A

FILTER LTE **TF-007A**

The TF-007A filter is used to suppress LTE signals that may cause interference in terrestrial TV installations.



Working frequency band:	5 ... 1000 MHz
Stop-band:	240 ... 470 MHz 694 ... 3000 MHz
Return loss:	> 23 dB @ 350 MHz > 25 dB @ 703 MHz > 25 dB @ 733 MHz > 35 dB @ 1000 MHz
Insertion loss:	< 0.3 dB @ 5 MHz < 2 dB @ 240 MHz < 3 dB @ 470 MHz < 4 dB @ 694 MHz
Main features:	• It is equipped with 24V/100mA DC pass • Shielded • F type connectors • Mast mounting diameter
Weight:	0.17 kg
Dimensions:	89 x 107 x 43 mm
Guarantee:	2 years