

Code: RUD-3-DES

PROXIMITY READER **RUD-3-DES** ROGER

Proximity card reader connected to the computer's USB port for quick and convenient reading cards, keyfobs, etc. in RACS (min. ver 4.4.6), VISO 1.x, Roger MiniReader ver. 1.2 systems. For those who want to integrate RUD-3-DES with other software, the manufacturer provides a DLL library.

A practical magnetic stand is included with the device.



Cards support:	<ul style="list-style-type: none"> • 13.56 MHz S50, • 13.56 MHz S50 DESFire (EV1, EV2)
Reading distance of prox-keys:	<ul style="list-style-type: none"> ≤ 6 cm 13.56 MHz S50 Classic ≤ 3 cm 13.56 MHz S50 DESFire
Communication:	USB - HID
Power supply:	from USB port
Supported operating systems:	Windows
Main features:	<ul style="list-style-type: none"> • Reads card numbers: CSN, SSN, MSN, DESFire File • Writes card numbers: SSN, MSN, DESFire File • LEDs indicating device operation state • Configuration through USB (RogerVDM) • Software SDK • A practical magnetic stand is included with the device
Weight:	0.024 kg (without stand)
Dimensions:	101 x 31 x 15 mm (without stand)
Manufacturer / Brand:	ROGER
Guarantee:	3 years