

Code: ARC3000H-FW2(868)

WIRELESS ALARM CONTROL PANEL **ARC3000H-FW2(868)** DAHUA

The ARC3000H-FW2(868) wireless alarm control panel supports max. 150 devices. In addition, the device allows you to handle max. 6 wireless sirens and up to 64 remote control keyfobs.



Number of supported wireless detectors:	max. 150 pcs
Number of supported remote control keyfobs:	max. 64 pcs
The RFID cards/keyfobs support:	—
Number of supported wireless sirens:	max. 6 pcs
Operating frequency range of the wireless devices:	868 MHz
Operating range in open area:	max. 2000 m
Keyboard included:	—
Expander included :	—
Built-in modules:	<ul style="list-style-type: none"> • LAN 10/100Mb • Wi-Fi 2.4 GHz / 5 GHz • GSM (GPRS, 3G, 4G LTE) - It supports push messages, SMS text notifications, and audio notifications via the phone
Access from PC:	<ul style="list-style-type: none"> • DMSS application - for the end user • COS Pro application - for the installer
Mobile phones support:	✓
Main features:	<ul style="list-style-type: none"> • Bidirectional communication • Two SIM cards support • Support for video events via a mobile client and email • Configuration via the www client, mobile client or software • LED indication
Power supply:	12 V DC / 1.5 A (power adapter included)
Housing:	Plastic
Color:	White



DATA SHEET

Operation temp:	-10 °C ... 55 °C
Weight:	0.39 kg
Dimensions:	163 x 163 x 32 mm
Manufacturer / Brand:	DAHUA
Guarantee:	3 years