

Code: HY-SA21A-W2(868)

## WIRELESS SMOKE DETECTOR **HY-SA21A-W2(868)** DAHUA

Wireless smoke detector, which is designed to early detection of a developing fire. Besides sending the information to the control panel, the HY-SA21A-W2(868) detector can warn of the danger of using the built sound alarm.

The HY-SA21A-W2(868) supports the other devices compatible with wireless DAHUA system.



Support:	Wireless alarm systems DAHUA
Detection:	smoke
Alarm signaling:	<ul style="list-style-type: none"> <li>• Buzzer <math>\geq 85</math> dB @ 3 m</li> <li>• LED indicator - red</li> <li>• Signal to control panel</li> </ul>
Frequency band:	868 MHz
Radio communication range (at open area):	1000 m
Power supply:	1 x battery CR123A 3 V (included)
Backup time:	~ 3 years
Current consumption at standby mode:	$\leq 35$ $\mu$ A
Maximal current consumption:	$\leq 35$ mA

Main features:	<ul style="list-style-type: none"><li>• Smoke detection - Chamber with photoelectric sensor</li><li>• Frequency hopping against jamming for reliable transmission</li><li>• Alarm mute function</li><li>• Bidirectional communication</li><li>• AES-128 data encryption</li><li>• Ceiling mounting</li><li>• Tamper detection - opening the enclosure</li></ul>
Color:	White
Operation temp:	-10 °C ... 55 °C
Weight:	0.13 kg
Dimensions:	Ø 98 x 43 mm
Manufacturer / Brand:	DAHUA
Guarantee:	2 years