

Code: ARD324-W2(868)

WIRELESS MAGNETIC CONTACT **ARD324-W2(868)** DAHUA

The ARD324-W2(868) wireless detector (magnetic contact) is used to protection the windows and doors.



Support:	Wireless alarm systems DAHUA
Detection:	Opening the door or window
Break distance:	~ 40 mm
Alarm signaling:	Signal to control panel
Frequency range:	868 MHz
Radio communication range (at open area):	max. 1200 m (open area)
Alarm inputs:	1 pcs NO / NC / Pulse counter
Battery:	1 x CR123A 3 V (included)
Backup time:	~ 3 years
Current consumption:	60 mA



DATA SHEET

Main features:	<ul style="list-style-type: none">• Tamper protections• Low battery level alarm• Detection of shocks and vibrations associated with attempts to force a door or window• Bidirectional communication• AES128 data encryption• Frequency hopping against jamming for reliable transmission• Test mode• Temperature measurement in the range: -15°C ... +65°C• thermal protection• Configuration using the application• Cloud update
Color:	White
Operation temp:	-10 °C ... 55 °C
Weight:	<ul style="list-style-type: none">• 0.034 kg - Transmitter• 0.034 kg - Magnet
Dimensions:	<ul style="list-style-type: none">• 100 x 21 x 21 mm - Transmitter• 100 x 21 x 21 mm - Magnet
Manufacturer / Brand:	DAHUA
Guarantee:	2 years