

Code: LR1002-1ET-V3

EXTENDER ETHERNET+PoE **LR1002-1ET-V3** TRANSMITTER DAHUA

The LR1002-1ET-V3 extender allows to increase a distance of transmission of the data and PoE 802.3 at/af, ePoE powering via coaxial cable.

The device operates from the camera side.

WARNING! The PoE power is supplied together with data on pairs 1, 2 and 3, 6.



LAN ports:	1 pcs RJ45
Transmission ports:	1 pcs BNC
Transmission speed:	10 / 100 Mbps
Transmission range:	max. 1000 m @ 10 Mbps max. 400 m @ 100 Mbps The range of data transfer and power supply is strongly dependent on the cable used and the power required to supply the receiver
Protections:	Overvoltage
Main features:	<ul style="list-style-type: none"> • Plug & Play • MDI/MDI-X auto detection feature - auto detecting the data transmission mode • Support for IP cameras and network devices • Easy installation - doesn't require any configuration of IP nor MAC address • Power supply PoE - pins 1, 2 and 3, 6 • The device operates from the camera side • Possibility to mount on a wall, or on the DIN TS-35 rail • UTP cable length to the camera max. 2 m
Power supply:	<ul style="list-style-type: none"> • ePoE • PoE (802.3af/at)
Weight:	0.07 kg
Dimensions:	79 x 64 x 23 mm
Manufacturer / Brand:	DAHUA
Guarantee:	3 years

