

Code: DY-10020A-PRO

POWER GENERATOR **DY-10020A-PRO** 10 kW SENCi Dynamo

A power generator equipped with a starter is ideal as a power source in the event of a power outage in the network or as a substitute power source in a company, on a construction site, at home or in a workshop. The genset engine's rubber stabilizers and engine mounts dampen vibrations and minimize noise.

Attention! The device is not designed for continuous 24/7 operation. In case of long operation, the power generator should not be loaded with more than 75% of the nominal power.



Nominal power:	10 kW , 3 kW - for a single-phase socket
Maximum power:	11 kW
Output voltage:	<ul style="list-style-type: none"> • 230 V AC, • 400 V AC
Number of outlets:	1 pcs - three-phase, 32 A IEC 60309 , 2 pcs - single-phase, 16 A CEE 7/4 (Schuko)
Output frequency:	50 Hz
ATS compatible:	✓
Built-in voltmeter:	✓
Voltage stabilization:	AVR
Frequency measurement in Hz:	✓
Measuring the number of engine hours:	✓
12V DC output:	✓
Engine power:	18 HP



DATA SHEET

Engine capacity:	688 cm ³
Engine type:	SV690 - V-shaped, 2-cylinder, gasoline, air cooled
Starting the engine:	Electric - starter motor
Noise level during operation:	90 dB
Average fuel consumption:	5.6 l/h
Fuel tank capacity:	45 l
Fuel gauge:	✓
Main features:	<ul style="list-style-type: none">• Low oil level indicator light• Overload protection• Display of operating parameters : voltage, frequency, engine hours since the engine was last started, total engine hours• High mobility of the device thanks to the attached wheels• 12V / 36Ah battery - included
Color:	Black + Red
Weight:	170 kg
Dimensions:	730 x 600 x 780 mm
Manufacturer / Brand:	SENCI / Dynamo
Guarantee:	2 years