

Code: ATLO-SW1-EWELINK

SMART LED LIGHTING CONTROLLER **ATLO-SW1-EWELINK** Wi-Fi, eWeLink

The ATLO-SW1-EWELINK controller allows you to control LED lighting wirelessly via the application or via a connected button. For proper functioning of the device, it is necessary to connect it to the Wi-Fi network with Internet access.

Beyond direct control, the device has the ability to program the on and off schedule and linking to different system events. It is possible to create action scenarios with other devices. Voice control allows you to control the device via voice commands from Amazon Alexa or the Google Assistant (Internet access required).

eWeLink is an international home automation platform that connects thousands of products made by different manufacturers. The system can support all the most popular communication protocols such as Wi-Fi, Zigbee, Bluetooth.

Attention! Controlling the device and schedule settings is possible if the device has access to the Internet.



Application:	switching devices on/off
Number of channels:	1
Power supply:	100 ... 240 V AC, 50 / 60 Hz
Maximal total load:	250 W
Total maximal current:	10 A
Number of inputs:	1
Number of outputs:	1
Connector type:	screw terminals
Wireless:	Wi-Fi, 2.4 GHz - IEEE 802.11 b/g/n
Radio communication range:	< 100 m (open area)
Mobile phones support:	<ul style="list-style-type: none"> • Android: Free application eWeLink • iOS (iPhone): Free application eWeLink

Main features:	<ul style="list-style-type: none">• Local control by physical button ,eWeLink :• schedule,• timer,• Setting scenarios by different events,• remote access,• voice control ,
Housing:	Plastic
"Index of Protection":	IP20
Color:	White
Operation temp:	-10 °C ... 40 °C
Weight:	0.03 kg
Dimensions:	44 x 39 x 22 mm
Manufacturer / Brand:	ATLO
Guarantee:	2 years