

Code: HNB-B16/1N/003

## RESIDUAL CURRENT CIRCUIT BREAKER **HNB-B16/1N/003** ONE-PHASE, AC TYPE 30 mA 16 A EATON

AC type residual current circuit breaker with B curve and rated residual current  $I_{\Delta n} = 30\text{mA}$ . The HNB-B16/1N/003 circuit breaker is compatible to DIN TS-35 rail mounting system.



Device type:	Residual Current Circuit Breaker, One-phase, AC type, B curve
Rated sensitivity:	30 mA
Rated current:	16 A
Number of poles:	2
Breaking capacity:	6000 A
Rated voltage:	230 V AC / 50 Hz
Connectors type:	screw terminals
Wire gauge:	1.5 mm <sup>2</sup> - 25 mm <sup>2</sup>
Main features:	<ul style="list-style-type: none"> <li>• Contact position indicator</li> <li>• Can be connected with using the supply busbars fork-type or prong-type</li> <li>• Possibility of sealing</li> </ul>
Housing:	Plastic, DIN, TS-35 rail mounting
Width in 17.5 mm modules:	2



# DATA SHEET

---

Weight:	0.196 kg
Dimensions:	84 x 35.5 x 73 mm
Manufacturer / Brand:	EATON
Guarantee:	2 years