

Code: GAR-SAT/2RJ

FINAL SOCKET **GAR-SAT/2RJ** R-TV SAT+RJ45+RJ11

Outlet combines the functions of radio-tv-satellite socket and a socket for telephone and Internet connection.



| | |
|------------------------|--|
| Mount: | Flush-mounted |
| TV frequency range: | 5 ... 68 MHz 174 ... 862 MHz |
| Radio frequency range: | 88 ... 125 MHz |
| SAT frequency range: | 950 ... 2250 MHz |
| TV tap attenuation: | 2.0 ... 2.5 dB |
| Radio tap attenuation: | 2.0 dB |
| SAT tap attenuation: | 2.5 ... 3.5 dB |
| Main features: | <ul style="list-style-type: none"> • Socket RJ 45 - 8 pcs pin • Socket RJ 11 |
| Weight: | 0.140 kg |
| Guarantee: | 2 years |