

Code: MP-4/R

## ADJUSTABLE AUDIO MODULE **MP-4/R**



MP-4/R is designed for listening to the outside sounds. The device has a gain control PCB potentiometer. The device has a screw terminal (ARK) to connect the devices.

Bandwidth:	20 Hz ... 18 kHz
S/N ratio:	≥ 60 dB
Operation area:	5 ... 150 m <sup>2</sup>
Gain adjustment:	1x ... 500x
Power supply:	12 V DC
Current consumption:	5 mA
Housing:	Plastic
Dimensions:	50 x 24 x 20 mm
Weight:	0.01 kg
Manufacturer / Brand:	DELTA
Guarantee:	<b>3 years</b>