

Code: FUT092

## REMOTE CONTROL FOR LED LIGHTING CONTROLLERS **FUT092** 2.4 GHz, MONO, CCT, RGB, RGBW, RGCCT (RGBWW) MiBOXER / Mi-Light

The FUT092 remote control is designed to control LED lighting controllers of the FUT035S / FUT036S / FUT038S / FUT039S / WL5 series. Communication between devices takes place using radio waves in the 2.4 GHz frequency band. The remote control is equipped with touch buttons, enabling independent control of switching on, brightness and color of light in up to 4 zones.

The MiBOXER controllers allow you to divide the lighting into up to 4 zones and independently control the zones using the remote control. Thanks to the repeater function, if the distance  $\leq 30\text{m}$  is kept between the controllers, it is possible to transmit the control signal to controllers that are beyond the direct range of the remote control.



Application:	Works with LED lighting : (RGB/RGBW/RGCCT/CCT/MONO) 12-24V LED strips
Number of channels:	4
Wireless:	2.4 GHz
Radio communication range (at open area):	30 m
Main features:	Touch control keys
Power supply:	2 x 1.5V, type AAA/LR03 battery (not included)
Housing:	Plastic
Color:	White
Operation temp:	-20 °C ... 60 °C
Weight:	0.07 kg (without battery)
Dimensions:	137 x 55 x 21 mm
Manufacturer / Brand:	MiBOXER / Mi-Light
Guarantee:	2 years