

Code: INT-KLCDL-BL

## KEYPAD FOR ALARM CONTROL PANEL **INT-KLCDL-BL** SATEL

The INT-KLCDL-BL keypad is intended for daily operations and programming the INTEGRA series alarm control system. With the LCD display showing text messages, even advanced functionalities of the alarm control unit are simple and convenient.



Support:	INTEGRA, CA-64
Main features:	<ul style="list-style-type: none"> <li>• Blue backlight of the keys</li> <li>• 2 Inputs</li> <li>• easy operation of the multi-zone systems</li> <li>• LEDs indicating device operation state</li> <li>• Alarms: keypad hold-down PANIC, FIRE and AUX</li> <li>• Buzzer for acoustic signaling of some system events</li> <li>• Panel communication loss indication</li> <li>• RS-232 port allows to programming using the PC with GUARDX software installed</li> <li>• Microswitch as tamper contact</li> </ul>
Power supply:	12 V DC
Current consumption:	max. 147 mA
Operation temp:	-10 °C ... 55 °C
Weight:	0.21 kg
Dimensions:	145 x 115 x 29 mm
Manufacturer / Brand:	SATEL
Guarantee:	2 years