

Code: SD-504

TV/SAT SPLITTER **SD-504**

The SD-504 splitter is used in multiswitch systems to distribute a signal from multiswitch bus. Additionally, the splitter also distributes terrestrial TV signals. The splitter is equipped with DC-transition switch that in "ON" position passes DC voltage through "H" paths to both branches. In "OFF" position it runs voltage to one path only.



Frequency range:	950 ... 2400 MHz - SAT, 5 ... 862 MHz - TV
Connection loss:	4 dB - SAT, 4 dB - TV
Isolation between outputs:	> 30 dB
DC-transition:	max. 2 A
Operation temp:	-20 °C ... 50 °C
Weight:	0.39 kg
Dimensions:	126 x 135 x 30 mm
Guarantee:	2 years