

Code: AMBER-2E

PIR DETECTOR **AMBER-2E** SATEL

Digital passive PIR detector. The device can interface with any alarm control panel which supports the 2EOL/NC (2 x 1.1 k Ω) type detectors.



Application:	Indoor
Pyroelectric sensor:	Double
Sensor type:	Passive Infra Red (PIR)
Range:	12 x 20 m
Sensitivity adjustment:	2 - step
Pet immunity:	—
Alarm time:	2 s
Digital temperature compensation:	✓
Target speed range:	0.3 ... 3 m/s
Power supply:	12 V DC / 3 mA
Main features:	EOL resistors 2 x 1.1 k Ω 2EOL/NC
Operation temp:	-30 °C ... 55 °C
Weight:	0.03 kg
Dimensions:	49 x 66 x 36 mm
Main features:	2EOL/NC
Manufacturer / Brand:	SATEL



DATA SHEET

Guarantee:	2 years
------------	---------