

Code: INT-IORS

## EXPANDER **INT-IORS** 8 INPUTS/8 OUTPUTS SATEL

The device allows to extend the control panel with 8 additional inputs operating the NO, NC, EOL, 2EOL configurations and 8 programmable relay outputs. INT-IORS is designed to mount on the DIN 35 mm rail.



|                              |                               |
|------------------------------|-------------------------------|
| Support:                     | INTEGRA                       |
| Number of inputs:            | 8 pcs - programmable          |
| Number of outputs:           | 8 pcs - programmable          |
| Tamper output:               | —                             |
| Outputs type:                | Relay                         |
| Support configurations:      | NO, NC, EOL, 2EOL/NO, 2EOL/NC |
| Relay switching current:     | max. 16 A                     |
| Relay switching voltage:     | max. 250 V AC                 |
| Maximal current consumption: | 285 mA                        |
| Power supply:                | 12 V DC                       |
| Operation temp:              | -10 °C ... 55 °C              |
| Weight:                      | 0.3 kg                        |
| Dimensions:                  | 122 x 92 x 58 mm              |
| Manufacturer / Brand:        | SATEL                         |
| Guarantee:                   | 2 years                       |