

Code: TOPAZ

PIR DETECTOR **TOPAZ** SATEL

Digital passive PIR detector. The device can interface with any alarm control panel which supports the NC, 2EOL/NC (2 x 1.1 kΩ) type detectors.



Application:	Indoor
Pyroelectric sensor:	Double
Sensor type:	Passive Infra Red (PIR)
Range:	15 x 14 m
Sensitivity adjustment:	2 - step
Pet immunity:	—
Alarm time:	2 s
Maximal outputs load:	40 mA / 16 V DC
Digital temperature compensation:	✓
Main features:	2EOL/NC, NC configurations support
Power supply:	12 V DC / 8 mA
Operation temp:	-10 °C ... 55 °C
Target speed range:	0.3 ... 3 m/s
Weight:	0.04 kg
Dimensions:	52 x 81 x 33 mm
Manufacturer / Brand:	SATEL



DATA SHEET

Guarantee:

2 years