


Code: AWZ-101

BUFFERED POWER SUPPLY TRANSFORMER **AWZ-101**

The buffered power supply adapter is designed to powering control panels, sensors, code locks, cameras, consoles, intercoms and other alarm system equipment.
Please pay attention for proper cooling conditions of the power adaptor during work!



Adapter type:	Transforming
Input voltage:	230 V AC
Output voltage:	12.8 V ... 13.8 V (buffer operation)
Max. output current (total):	1 A
Battery charging current:	0.1 A
Power:	18 W
Number of outputs:	1
Protections:	• Short-circuit • Overload • Overvoltage • Overheat • Tamper • Reverse polarity connection
Adapter operation control:	• AC input voltage presence indication AC • DC output voltage presence indication DC
Place for battery:	12V/7Ah
Max. battery dimensions:	180 x 100 x 80 mm
Weight:	2.45 kg
Dimensions:	235 x 205 x 85 mm
Manufacturer / Brand:	PULSAR



DATA SHEET

Guarantee:

2 years