

Code: OR-MA-701

PIR DETECTOR WITH AUDIO SIGNAL **OR-MA-701**

The OR-MA-701 is dedicated to the control of the entrance doors, storage facilities and to protect children against dangerous places. The device informs by audio signal (type: gong or siren) about detection of motion within the detector zone.



Application:	Indoor
Sensor type:	Passive Infra Red (PIR)
Range:	4 ... 5 m
Alarm signaling:	selectable by switch : <ul style="list-style-type: none"> • Gong • Alarm siren ~ 85 dB/m
Sensitivity adjustment:	—
Pet immunity:	—
Battery power supply:	<ul style="list-style-type: none"> • 6 V DC / 300 mA (power adapter not included) • 4 x battery LR6 (AA) (not included)
Operation temp:	0 °C ... 40 °C
Weight:	0.13 kg
Dimensions:	72 x 82 x 122 mm
Manufacturer / Brand:	ORNO
Guarantee:	2 years