

Code: OR-CR-213

## HANDS-FREE SWITCH **OR-CR-213** AC 230V

A sensor switches an electrical circuit on when detects a movement. Switching off is after detection a next move by sensor. The OR-CR-213 is ideal for use in living room, kitchen, bedroom, eg. for illuminating mirrors, wardrobes, etc.



Application:	Internal
Detection method:	Motion Detection
Range:	5 ... 6 cm
Main features:	<ul style="list-style-type: none"> <li>• Non-contact switching on and off.</li> <li>• Switch function.</li> <li>• Works with LED lighting</li> </ul>
Power supply:	110 V ... 240 V AC @ 50Hz / @ 60Hz
Maximal load:	800 W, 500 VA
Nominal load current:	5 A
"Index of Protection":	IP20
Operation temp:	-20 °C ... 40 °C
Weight:	0.06 kg
Dimensions:	<ul style="list-style-type: none"> <li>• 35 x 78 x 19 mm - device</li> <li>• Ø 17 x 15 mm - detector</li> <li>• Ø 12.5 mm - Mounting hole diameter for the sensor</li> </ul>
Manufacturer / Brand:	ORNO
Guarantee:	2 years