

Code: PZU-4810-D2

CONVERTER MODULE **PZU-4810-D2** DC/DC

Inverter module increasing the voltage. The PZU-4810-D2 device converts the input voltage to the 8V ... 48V DC value.



Type:	Increasing the voltage, DC/DC
Number of inputs:	1
Number of outputs:	1
Power voltage:	8 ... 36 V DC
Output voltage:	8 ... 48 V DC
Output voltage adjustment:	Multi-turn precision potentiometer adjustment (27 rotations)
Output current:	5 A (max)
Power:	<ul style="list-style-type: none"> • 100 W (max) • 48 W (continuous operation)
Minimal voltage difference between out and in:	0 V
Protections:	<ul style="list-style-type: none"> • Short-circuit - Glass Fuse • Overheat > 80 °C • Reverse polarity connection
Main features:	<ul style="list-style-type: none"> • DIN, TS-35 rail mounting • LED indication - Input voltage, Output voltage
Application:	<ul style="list-style-type: none"> • to cameras powering • to cameras powering PoE • to cameras with thermostat powering
Weight:	0.12 kg



DATA SHEET

Dimensions:	37 x 97 x 58 mm
Manufacturer / Brand:	DELTA
Guarantee:	3 years

