

Code: INT-SZ-BL

## CODE LOCK **INT-SZ-BL** SATEL

The keypad basing on microprocessor technology is designed to alarm control panel support. The status indication is showed by LEDs and acoustic signals.



Support:	INTEGRA
Maximum current switched over by relay at DC 24V:	max. 2 A
Main features:	<ul style="list-style-type: none"> <li>• relay for electromagnetic lock/electric strike</li> <li>• door control input</li> <li>• Alarms: keypad hold-down PANIC, FIRE and AUX</li> <li>• Microswitch as tamper contact</li> <li>• LEDs indicating device operation state</li> <li>• Blue backlight of the keys</li> </ul>
Power supply:	12 V DC
Current consumption:	max. 66 mA
Operation temp:	-10 °C ... 55 °C
Weight:	0.11 kg
Dimensions:	80 x 126 x 23 mm
Manufacturer / Brand:	SATEL
Guarantee:	2 years