# DATA SHEET

### Code: INT-KSG-WSW

## SENSORIC KEYPAD FOR ALARM CONTROL PANEL **INT-KSG-WSW** SATEL

The INT-KSG-WSW sensoric keypad does not only stand for attractive design, but also for simplification for the daily operation of advanced alarm systems and home automation using the functionalities of the INTEGRA control units.
With the MAKRO functions, a whole sequence of actions can be performed through a single command. With the LCD display showing text messages, even advanced functionalities of the alarm control unit are simple and convenient.

| | |
|---|---|
| Support: | INTEGRA, CA-64 |
| Main features: | • Large, easily readable LCD with backlight displaying detailed information on system state<br>• 2 Inputs<br>• LEDs indicating device operation state<br>• customizable standby screen with possibility of individual set of displayed information<br>• 4 extra menus (up to 16 items each) and quick access functions defined by the installer<br>• MAKRO features that activates sequence of actions with a single key<br>• individual keypress feedback with LED and beep<br>• easy operation of the multi-zone systems<br>• Alarms: keypad hold-down PANIC, FIRE and AUX<br>• Bbuzzer for acoustic signaling of some system events<br>• Panel communication loss indication<br>• RS-232 port allows to programming using the PC with GUARDX software installed<br>• Microswitch as tamper contact |
| Power supply: | 12 V DC |
| Current consumption: | max. 175 mA |
| Color: | White + Silver |
| Operation temp: | -10 °C ... 55 °C |
| Weight: | 0.31 kg |

| Dimensions: | 143 x 156 x 23 mm |
| --- | --- |
| Manufacturer / Brand: | SATEL |
| Guarantee: | 2 years |