

## Warning!

Please read the user manual included in this work as it contains important information related with safety of installation and use of the device.

Only persons who read the user manual may use the device.

The user manual must be kept because it may be required in the future. The device is to be used exclusively for purposes specified in this user manual.

The device must be unpacked prior to starting-up. After removing the packaging make sure the device is in working order.

If the product has defects, it should not be used until it is repaired.

The product is intended for use at home and commercial use and may not be used for other than intended use.

The manufacturer is not liable for damages resulting from not adhering to the rules contained in the user manual, therefore, we recommend to follow the aforementioned safety rules for operation and maintenance of the device. In this way you will ensure yourself safety and avoid causing damage to the device.

The manufacturer and the supplier are not liable for losses or damages arising out of the product, including financial or intangible losses, loss of profits, income, data, pleasure from use of the product or other products related with it - indirect, incidental or consequential loss or damage. The above provisions apply whether the loss or damage concerns:

1. Deterioration of quality or the lack of operation of the products or products related with it due to damage as well as the lack of access to the product when it is undergoing repair, which results in stoppage the loss of user's time or a break in business activity;
2. Improper results of operation of the product or products related with it;
3. It applies to losses and damages according to any legal category, including negligence and other losses, termination of a contract, expressed or implied guarantee and strict liability (even if the manufacturer or the supplier was notified about the possibility of occurrence of such damages).

### Safety measures:

Particular attention at designing was directed to quality standards of the device where ensuring safety of operation is the most important factor.

The device must be secured against contact with caustic, staining and viscous fluids.

The device was designed in such a way that it restarts operation when power supply is restored after a break.

**Attention! We recommend using protections to further protect the device from possible overvoltages in installations. Surge protectors are effective protection against accidental pass to the device voltages higher than the rated. Damages caused by pass the voltages higher than specified in manual, are not under warranty.**

Turn off the device before transporting it.

Prior to connecting the device to a power source check whether the supplied voltage is consistent with rated voltage specified in the user manual.

### Proper product disposal:

A marking of a crossed out waste bin indicates that the product may not be disposed together with other household waste in the entire EU. To avoid possible damage to the natural environment of health due to uncontrolled waste disposal, therefore, it should be handed over for recycling, propagating in this way sustainable use of natural resources.

To return a worn-out product, use a collection and disposal system of this type of equipment or contact a seller from whom it was purchased. He will then be recycled in an environmentally-friendly way.

IP camera equipped with very good high resolution sensor. Due to above it is perfect solution for surveillance systems requiring persons or vehicles recognition. Thanks to the "Starlight" technology used, the camera only needs very low lighting to obtain a clear color image.

The used Wi-Fi module allows to remote communication with camera for max. distance up to 50 m. For a few models of IP cameras working at 4Mpx resolution we recommend to use of network with 1Gb/s bandwidth.





# User Manual

Code: SD22204UE-GN-W

IP SPEED DOME CAMERA OUTDOOR **SD22204UE-GN-W** Wi-Fi, - 1080p 2.7 ... 11 mm DAHUA


Standard:	TCP/IP
Sensor:	1/2.8 " STARVIS™ CMOS
Matrix size:	2.1 Mpx
Resolution:	1920 x 1080 - 1080p , 1280 x 960 - 1.3 Mpx , 1280 x 720 - 720p
IR illuminator:	—
Lens:	2.7 ... 11 mm
View angle:	• 113 ° ... 30 ° (manufacturer data) • 105 ° ... 35 ° (our tests result)
Optical zoom:	x 4
Digital zoom:	x 16
Min. illumination:	0.005 Lux (color) 0.0005 Lux (B/W)
S/N ratio:	> 50 dB (AGC off)
Preset rotation speed:	• 100 °/s (horizontal) • 60 °/s (vertical)
Rotation speed (manual control):	• 0.1 °/s ... 100 °/s (horizontal) • 0.1 °/s ... 60 °/s (vertical)
Horizontal rotation range:	0 ° ... 355 - Rotation of the head is limited by stops
Vertical rotation range:	0 ° ... 90 °
Protocols:	DH-SD
RS-485 interface:	—
Number of presets:	300
Horizontal scan:	✓
Route settings:	5
Image compression method:	H.265 / H.264 / MJPEG
Audio:	—
Bitrate:	448 ... 8192 kbps
Alarm inputs / outputs:	—
Main stream frame rate:	25 fps @ 1080p
Network interface:	10/100 Base-TX (RJ-45)
Network protocols:	IPv4/IPv6, HTTP, HTTPS, SSL, TCP/IP, UDP, UPnP, ICMP, IGMP, SNMP, RTSP, RTP, SMTP, NTP, DHCP, DNS, PPPoE, DDNS, FTP, IP Filter, QoS, Bonjour, IEEE 802.1x
Memory card slot:	Micro SD memory cards up to 128GB support (possible local recording)
WEB Server:	Built-in, NVR compliance
Max. number of on-line users:	20

ONVIF:	18.06
Mobile phones support:	Port no.: 37777 or access by a cloud (P2P) • Android: Free application <a href="#">DMSS</a> • iOS (iPhone): Free application <a href="#">DMSS</a>
Main features:	<ul style="list-style-type: none"> <li>• Wi-Fi module - IEEE 802.11 b/g/n, Range : 50 m (open area) ; Antenna - SMA socket</li> <li>• WDR - 120 dB - Wide Dynamic Range</li> <li>• 2D-DNR, 3D-DNR - Digital Noise Reduction</li> <li>• F-DNR (Defog) - Reduction of image noise caused by precipitation</li> <li>• ROI - improve the quality of selected parts of image</li> <li>• BLC/HLC - Back Light / High Light Compensation</li> <li>• Configurable Privacy Zones</li> <li>• Motion Detection</li> <li>• Sharpness - sharper image outlines</li> <li>• ICR - Movable InfraRed filter</li> <li>• Mirror - Mirror image</li> <li>• AGC - Automatic Gain Control</li> <li>• Day/night mode</li> <li>• IVS analysis : face detection, crossing the line (tripwire), intrusion, abandoned/missing object</li> </ul>
Power supply:	12 V DC / 460 mA
Power consumption:	≤ 5.5 W
Housing:	Speed Dome, Metal
Color:	White
Supported languages:	Polish, English, Czech, French, Spanish, Dutch, German, Portuguese, Russian, Italian
Operation temp:	-30 °C ... 60 °C
"Index of Protection":	IP66
Vandal-proof:	IK10
Weight:	0.61 kg
Dimensions:	Ø 123 x 89 mm
Manufacturer / Brand:	DAHUA
Guarantee:	<b>3 years</b>

Camera view after remove the Dome cover:



Memory card slot:



Camera mounting dimensions:



See how to initialize DAHUA cameras:

:

In the kit:



# User Manual

Code: SD22204UE-GN-W

IP SPEED DOME CAMERA OUTDOOR **SD22204UE-GN-W** Wi-Fi, - 1080p 2.7 ... 11 mm DAHUA



## PACKAGE

Dimensions (L x W x H): 0x0x0 mm	Gross Weight: 0 kg
----------------------------------	--------------------